

SH-136B Digital Thermometer

Technical Data:

- .Range:-50~300°C or -58~572°F
- .Resolution:0.1°C/0.1°F
- .Accuracy: -20~100°C (-4~212°F), +/-1°C or +/-2°F
-40~-20°C (-40~-4°F) and 100~200°C (212~392°F),
+/-2°C or +/-4°F, other +/-2.5°C or +/-5°F
- .Voltage:1.5V,1pcs AAA battery
- .Sensor:L=1m;probe:10cm,stainless steel
- .Automatic power off after 10 mins
- .Sampling:1second.
- .Magnets on the back.
- .Calibration.

Key Function:

- .ON/OFF:turn on or off the LCD display ;
- .HOLD:to keep the display value on the screen for easy read;
- .MAX/MIN:to display the maximum temperature and minimum temperature,hold it 2 seconds to clear the memory;
- .°C/°F:to switch the unit display of temperature;
- .CAL:to correction temperature;

Operate:

- .After install battery,the screen display 888.8 ,then display the value of measure temperature.
- .Press ON/OFF button can turn on and turn off the display;press HOLD button keep the value on the screen for easy read;
- .Press MAX/MIN to display the memory of maximum or minimum value of temperature;hold the button 2 seconds to clear the memory.

Calibrate:

- .Put the sensor into the 0°C ice water mixture,when the screen display between -5°C to 5°C, hold CAL button 2 seconds,the screen display CAL 1second,after that screen display 0.0°C, calibration completed; If the value is not between -5°C to 5°C, hold CAL will display "Err" 1second,it mean error.After change the battery,it need redo calibrate.

Placing:

- .Put on the table;
- .Put on the wall with a hole on the back;
- .Put on the iron with the magnet on the back.